
TECHNICAL INFORMATION

WASHING MACHINES

4-023-0205

1. RESETTING OF WASHING MACHINE OR MINUTES SUMMING UP INSTEAD OF DEDUCTING ON WASHING MACHINES SIMPLE&LOGICAL AND PROLOGICAL

One of complaints concerning washing machines S&L and PROLOGICAL is resetting of washing programme or minutes summing up. The reason for this fault lies in electrical disturbances, caused by the electric motor. This is usually abolished by the RC link on tension rectifier, however the resistor can break down and the failure could not be abolished.

On washing machine S&L minutes are summing up for one whole cycle (e.g.: if it is in rinsing phase, returns for one complete rinsing).

On washer PROLOGICAL (WA 120-130), complete washing programme can get reset and than reactivated by repressing the STARTbutton.

In the event of burnt-out resistor on rectifier, replace the rectifier.

